



since 1971
the power to control

Fleischmann
unitro[®]
STÖRMELDESYSTEME

Collection alarm indication units FSB 08/16-48 -SA

for front panel installation, 8 - 48 signal inputs

Type designation:

FSB 16/08 (16) -SA

collective alarm indicating unit
for 8 or 16 signal inputs,
with new-value horn alarm
and LED-test

FSB 48/08 (16/24/32/40/48) -SA

collective alarm indicating unit
for 8 to 48 signal inputs in 8 input steps,
with new-value horn alarm
alarm and LED-test



Controls and displays

- Bright 5mm LED display
- Separate status indicator (green = Power ON)
- Easily exchangeable label strips
- Integrated small horn and function buttons

Parameterization

- With selector
- Quiescent / operating current, in groups of 8 (24-110V)


Electrical characteristics

- 8 - 48 signal inputs with LED-display red
- Continuous light during pending message
- No signal storage
- Integrated small horn
- EMC-values: UNITRO-Standard in accordance with EN 61000
- Group alarm change-over contact max. 5A 250V AC, 3A 30V DC

Mechanical characteristics

- Compact plastic junction housing 96 / 192 x 96 x 85 + 25mm. Degree of protection: front IP50
- Connection: Screw-type terminals, plug connection max. 2,5mm²

Connection diagram FSB 16 and FSB 48 -SA



Technical data:

- Type of construction:**
control board housing
96 / 192 x 96 x 85 + 25mm
(cutting for installation: 92 / 186 x 92 + 1mm)
- Degree of protection:**
front IP50, rear IP20
(front FSB 08/16 option IP54)
- Weight:**
FSB 16 approx. 400g
FSB 48 approx. 650g
- Climatically conditions:**
in accordance with UNITRO-Standard
- Connection:**
screw-type terminals/ plug connection
max. 2,5mm²
- Front panel buttons:**
acknowledge horn
LED test
- External button:**
acknowledge horn (normally open contact)
- Supply voltage:**
24V AC/DC, 60V DC ± 10 - 15% or
230V AC ± 10 - 15% or
60 / 110 / 220V DC, ± 10 - 15%
voltage-adapted
- Max. fuse:**
4A medium slow
- Minimum signal duration:**
DC: 10ms / AC:100ms
- Input level for signal inputs:**
24V AC/DC ± 10% - 15% max. 7mA
230V AC ± 10% - 15% max. 2,9mA
for special applications with high power loss:
60V DC ± 10% - 15% max. 7mA
110V DC ± 10% - 15% max. 6mA
220V DC ± 10% - 15% max. 6mA
voltage-adapted
voltage tolerance ±10%
- Power loss 100% ED:**
max. 2W + 8x 1,3W
attention: from 60V forced ventilation
power loss per signal: 60V DC 0,5W
110V DC 0,7W
220V DC 1,3W
- LED display:**
labeled with marking strips
alarm: red steady light
no alarm: LED off

power on LED = green steady light
- Relay outputs:**
1x group alarm and 1x horn contact,
potential-free change-over, max. 250V 5A
- Parameterization:**
with selector switch, in groups of 8:
quiescence- / operation current (24-110V)
- Leakage distances and clearances:**
in accordance with UNITRO-Standard
- EMC, immunity of interference:**
UNITRO-Standard,
in accordance with EN 61000



since 1971
the power to control

Combinations FSB -SA

FSB SA	Power supply	Input Card																			
	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8 / 16 Bay + power supply</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">24V AC/DC ± 10-15%</td> <td style="text-align: center;">230V AC ± 10-15%</td> </tr> </table> </td> </tr> <tr> <td style="text-align: center;">or</td> <td style="text-align: center;">+</td> </tr> <tr> <td style="text-align: center;">8 / 16 / 24 / 32 / 40 / 48 Bay + power supply</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">24V AC/DC ± 10-15%</td> <td style="text-align: center;">230V AC ± 10-15%</td> </tr> </table> </td> </tr> </table>	8 / 16 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">24V AC/DC ± 10-15%</td> <td style="text-align: center;">230V AC ± 10-15%</td> </tr> </table>	24V AC/DC ± 10-15%	230V AC ± 10-15%	or	+	8 / 16 / 24 / 32 / 40 / 48 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">24V AC/DC ± 10-15%</td> <td style="text-align: center;">230V AC ± 10-15%</td> </tr> </table>	24V AC/DC ± 10-15%	230V AC ± 10-15%	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 24V AC/DC ± 10-15%</td> </tr> </table> </td> <td style="text-align: center;">and/or</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 230V AC ± 10-15%</td> </tr> </table> </td> <td style="text-align: center;">and/or</td> </tr> </table>	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 24V AC/DC ± 10-15%</td> </tr> </table>	8xdigital IN 24V AC/DC ± 10-15%	and/or	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 230V AC ± 10-15%</td> </tr> </table>	8xdigital IN 230V AC ± 10-15%	and/or			
	8 / 16 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">24V AC/DC ± 10-15%</td> <td style="text-align: center;">230V AC ± 10-15%</td> </tr> </table>	24V AC/DC ± 10-15%	230V AC ± 10-15%																	
	24V AC/DC ± 10-15%	230V AC ± 10-15%																			
or	+																				
8 / 16 / 24 / 32 / 40 / 48 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">24V AC/DC ± 10-15%</td> <td style="text-align: center;">230V AC ± 10-15%</td> </tr> </table>	24V AC/DC ± 10-15%	230V AC ± 10-15%																		
24V AC/DC ± 10-15%	230V AC ± 10-15%																				
<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 24V AC/DC ± 10-15%</td> </tr> </table>	8xdigital IN 24V AC/DC ± 10-15%	and/or	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 230V AC ± 10-15%</td> </tr> </table>	8xdigital IN 230V AC ± 10-15%	and/or																
8xdigital IN 24V AC/DC ± 10-15%																					
8xdigital IN 230V AC ± 10-15%																					
<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8 / 16 Bay + power supply</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">48/60V DC ± 10-15%</td> <td style="text-align: center;">110/125V DC ± 10-15%</td> <td style="text-align: center;">220V DC ± 10-15%</td> </tr> </table> </td> </tr> <tr> <td style="text-align: center;">or</td> <td style="text-align: center;">+</td> </tr> <tr> <td style="text-align: center;">8 / 16 / 24 / 32 / 40 / 48 Bay + power supply</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">48/60V DC ± 10-15%</td> <td style="text-align: center;">110/125V DC ± 10-15%</td> <td style="text-align: center;">220V DC ± 10-15%</td> </tr> </table> </td> </tr> </table>	8 / 16 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">48/60V DC ± 10-15%</td> <td style="text-align: center;">110/125V DC ± 10-15%</td> <td style="text-align: center;">220V DC ± 10-15%</td> </tr> </table>	48/60V DC ± 10-15%	110/125V DC ± 10-15%	220V DC ± 10-15%	or	+	8 / 16 / 24 / 32 / 40 / 48 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">48/60V DC ± 10-15%</td> <td style="text-align: center;">110/125V DC ± 10-15%</td> <td style="text-align: center;">220V DC ± 10-15%</td> </tr> </table>	48/60V DC ± 10-15%	110/125V DC ± 10-15%	220V DC ± 10-15%	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 48/60V DC ± 10-15%</td> </tr> </table> </td> <td style="text-align: center;">and/or</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 110/125V DC ± 10-15%</td> </tr> </table> </td> <td style="text-align: center;">and/or</td> <td style="text-align: center;"> <table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 220V DC ± 10-15%</td> </tr> </table> </td> </tr> </table>	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 48/60V DC ± 10-15%</td> </tr> </table>	8xdigital IN 48/60V DC ± 10-15%	and/or	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 110/125V DC ± 10-15%</td> </tr> </table>	8xdigital IN 110/125V DC ± 10-15%	and/or	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 220V DC ± 10-15%</td> </tr> </table>	8xdigital IN 220V DC ± 10-15%
8 / 16 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">48/60V DC ± 10-15%</td> <td style="text-align: center;">110/125V DC ± 10-15%</td> <td style="text-align: center;">220V DC ± 10-15%</td> </tr> </table>	48/60V DC ± 10-15%	110/125V DC ± 10-15%	220V DC ± 10-15%																	
48/60V DC ± 10-15%	110/125V DC ± 10-15%	220V DC ± 10-15%																			
or	+																				
8 / 16 / 24 / 32 / 40 / 48 Bay + power supply	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">48/60V DC ± 10-15%</td> <td style="text-align: center;">110/125V DC ± 10-15%</td> <td style="text-align: center;">220V DC ± 10-15%</td> </tr> </table>	48/60V DC ± 10-15%	110/125V DC ± 10-15%	220V DC ± 10-15%																	
48/60V DC ± 10-15%	110/125V DC ± 10-15%	220V DC ± 10-15%																			
<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 48/60V DC ± 10-15%</td> </tr> </table>	8xdigital IN 48/60V DC ± 10-15%	and/or	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 110/125V DC ± 10-15%</td> </tr> </table>	8xdigital IN 110/125V DC ± 10-15%	and/or	<table border="1" style="width: 100%;"> <tr> <td style="text-align: center;">8xdigital IN 220V DC ± 10-15%</td> </tr> </table>	8xdigital IN 220V DC ± 10-15%														
8xdigital IN 48/60V DC ± 10-15%																					
8xdigital IN 110/125V DC ± 10-15%																					
8xdigital IN 220V DC ± 10-15%																					

